



SC-35

PMR446 / FRS
Two-way Radio


VOX


Noise
Reduction


Status
Display


Recording
Function

Sonice

SC-35

Function Characteristics

- Recording Function
- Emergency Alert
- One-Key Frequency
- TOT
- Scan
- VOX
- Busy Channel lockout
- Wireless Copy
- Digital/Analog Switchable

General Indicator

SPECIFICATION	TRANSMITTER		RECEIVER		
Frequency Range	400-480MHz	Output Power	High Power: 2W Low Power: 0.5W	Receive Sensitivity	≤-125dBm (12dB SINDA)
Channel Number	16	Frequency Stability	±2.5ppm	Audio Power	≥500mW
Bandwidth	12.5 KHz/25 KHz	Adjacent Channel Power	60dBm@12.5KHz	Rated Audio Distortion	≤5%
Operating Voltage	3.7V DC	FM Modulation	12.5KHz@11K0F3E	Receive Current	≤400mA
Battery Capacity	3000mAh	Transmission Current	≤1200mA		
Operating Temperature	-20°C to +50°C				
Antenna Impedance	50Ω				
Dimensions	93×54×36mm				

Standard Accessory



Email: info@soniceradio.com

Website: www.soniceradios.com